

PRS2-ZW Z-Wave Power Relay Switch

Powering a Greener, Simpler Lifestyle



- Small and compact profile
- Doubles as a Z-Wave repeater
- OTA firmware update capability

PRS2-ZW is a Z-Wave Power Relay Switch, allows users to remotely turn on/off the lights, electrical appliances or cut the power off in case of a malfunction at anytime, from anywhere.

Its small and compact profile provides the flexibility to be installed in flush mounted junction boxes, power sockets, or in the ceiling wall. PRS2-ZW also doubles as a Z-Wave repeater to further extend user's wireless communication range.

Integrated with a smart home security system to work with other devices and create customized scenes, schedules, or timer. Use the PRS2-ZW to control the lighting or heating, as well as emergency situations, to cut the power off after detecting a fire or flooding.

The extra convenience and safety provided by PRS2-ZW will help users manage their home environment more easily and with greater energy efficiency.

Features

- Connects directly to power cable
- Doubles as a Z-Wave repeater
- Small, compact profile for flexible installation
- LED status indicator
- Allows relay activation events to be integrated into other home automation activities, scenes, or schedules
- Over-the-Air (OTA) firmware update capability
- Extension terminal for connecting an external switch
- Function button for manual operation
- Compatible with other manufacturers' Z-Wave systems
- Suitable for residential and commercial premises

Specifications

Communication Protocol	Z-Wave Plus 500 Series
Frequency	868.40 MHz (EU) / 908.40 MHz (US)
Power Supply	110~230V, 50/60Hz
Maximum Load	10A
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	50mm x 51mm x 22mm