## **VESTA-107N**

BX-32-F1



## **Outdoor siren via radio**



- VESTA outdoor siren of 104dB at 1 meter
- Sounds of fire and theft
- Four levels of siren volume
- Programmable 3/5/10 minutes
- Tamper protection
- Configurable from App / Web installer



Reference / Model VESTA-107N / BX-32-F1

Specifications



## **Outdoor siren via radio**

## **Reference / Model**

**VESTA-107N / BX-32-F1** 

VESTA outdoor siren

The siren output level is 104dB at 1 meter

Differentiated sounds for each type of alarm: intrusion alarm, fire alarm and water leak alarm

Four selectable siren volume levels

Siren with programmable durations of 3/5/10 minutes

Arm / disarm beep, door chime and low battery status notifications

RF frequency. 868MHz

Compatible with VESTA F1 gateways / control panels

Tamper protection prevents unauthorized removal and tampering

Periodic monitoring signals to verify system integrity

Allows configurations from the App / Web installer

Power supply: 2 3V alkaline batteries

Battery life of up to 3 years

-25  $^{\circ}$  C  $\sim$  + 60  $^{\circ}$  C operating temperature

Relative humidity up to 85% (non-condensing)

IP65 waterproof and UV resistant housing

Dimensions: 180 (W) x 213.6 (H) x 57.7mm

Certified EN50131 Grade 2, ClassIV